

# CRYSTORAMA



Crystorama.com

LIGHTING THE WAY FOR SIXTY YEARS

## ASSEMBLY INSTRUCTION MODEL #5013EBCLMWP

### WARNING:




Electrical Danger



Turn Power Off


All electrical components must be installed by a licensed electrician in accordance with the National Electric Code and the appropriate local electrical codes.



You will need 3-Candelabra Base Bulb  
40 Watts recommended 60 Watts Max.

USE LED BULBS FOR EXTENDED USE

The fixture is Damp rated



### HOW TO INSTALL:

Place the fixture parts on a soft cloth-covered platform before installation of fixture.

1. Install the mounting bar onto the outlet box.
2. Decide the desired hanging height and adjust the chain to the correct length.
3. Raise the fixture up and do the wire connection. Attach the canopy over the mounting bar and secure with thread and nut.
4. Place the candle sleeve and bobèche over the socket.
5. Dress the crystals as illustrated.

### Crystal Sets

- A. 9 Sets. (1)14mm + (1)63mm  
B. 1 Piece. (1)14mm + AS8-30mm

**WARNING:** This product can expose you to Lead, which is known to the State of California to cause cancer and/or birth defects or reproductive harm. For more information go to [www.p65warnings.ca.gov](http://www.p65warnings.ca.gov)

# CRYSTORAMA



LIGHTING THE WAY FOR SIXTY YEARS

## ASSEMBLY INSTRUCTION MODEL #5013EBCLMWP

### Part Number

#### Part Numbers

- A. (2)-Wire Connector
- B. (1)-Mounting bar
- C. (2)-Mounting Screw
- D. (1)-Thread and nut
- E. (1)-Canopy (W5 3/4"xH1 1/4")-XSN5013EBCAN5.75IN
- F. (1)-Collar Loop & ring
- G. (1)-Chain (3.0mmx72")-XSN5013EBCHA3MM
- H. (1)-Fixture Loop-XSN5013EBLOOP
- I. (1)-Frame
- J. (3)-Metal candle sleeve;H2.17"-XSN5011EBMCDL2IN
- K. (3)-White plastic candle sleeve-XSN5011EBPCDL2IN
- L. (3)-Holder
- M. (3)-Bobeche ; Ø3 1/8"-XSN5011EBBOB3IN
- N. (3)-Arm
- O. (1)-Finial
- P. (9)-Eyelet-XSN5011EBEYE

